

## TECHNICAL DATA

# Fluke 9062 Motor and Phase Rotation Indicator



## Key features

- 3 phase indication
- Indication of phase rotation
- Indication of motor rotation direction
- Contact free determination of the rotation direction of running motors

## Product overview: Fluke 9062 Motor and Phase Rotation Indicator

### Unique phase rotation indicator with motor rotation ability

The unique Fluke 9062 provides rotary field and motor rotation indication with the benefits of contact-less detection. Purpose made for commercial and industrial environments, the Fluke 9062 provides rapid indication of 3 phase rotation using test leads supplied or can be used to determine motor rotation on synchronous and asynchronous 3 phase motors. The contact-less detection is ideal for use on motors where the shaft is not visible. The included test probes have a variable clamping range for safe contact, also in industrial sockets.

## Specifications: Fluke 9062 Motor and Phase Rotation Indicator

| Technical specifications              |                  |
|---------------------------------------|------------------|
| Voltage range                         | Up to 400 V      |
| Phase display                         | 120-400 V AC     |
| Frequency range                       | 2-400 Hz         |
| Operating timer                       | Continuous       |
| Environmental specifications          |                  |
| Operating temperature                 | 0 °C to 40 °C    |
| Operating altitude                    | Up to 2000m      |
| Humidity (without condensation)       | 15% to 80%       |
| Dust/water resistance                 | IP 40            |
| Safety specifications                 |                  |
| Electrical safety                     | EN 61010,        |
|                                       | EN 61557-7       |
| Overvoltage category                  | CAT III, 300 V   |
| Mechanical and general specifications |                  |
| Size                                  | 124 x 61 x 27 mm |
| Weight                                | 1 x 9 V          |
| Batteries                             | 1 x 9 V          |
| Warranty                              | 2 years          |

## Ordering information



### Fluke 9062

Fluke 9062 Motor and Phase Rotation Indicator

- Test leads (3)
- Test probes (3)
- Alligator clips (3)
- Battery, 9 V
- User manual

**Fluke.** *Keeping your world up and running.®*

**Fluke (UK) Ltd.**  
52 Hurricane Way  
Norwich, Norfolk  
NR6 6JB  
United Kingdom  
Tel.: +44 (0)20 7942 0708  
E-mail: [cs.uk@fluke.com](mailto:cs.uk@fluke.com)  
[www.fluke.com/en-gb](http://www.fluke.com/en-gb)

©2026 Fluke Corporation. All rights reserved.  
Data subject to alteration without notice.  
07/2026

**Modification of this document is not permitted  
without written permission from Fluke  
Corporation.**